



# OMNICARE OUTSTATION

## EMERGENCY TELEPHONE - GREEN - PUSH OR LOCK DOOR

### VIGIL *OmniCare*

The OmniCare system offers a choice of outstation units which can be wired on the same loop from the control panel.

The emergency/steward telephone unit is one of the options available on this versatile system.

#### FEATURES:

- Full duplex speech.
- Self-powered from ring circuit.
- Green finish.
- Rugged red handset with hearing aid compatible earpiece and loudspeaker.
- Hands free use.
- Door latch initiates call.
- Push catch or slot lockable door.
- Conference facility (via master control panel).
- Surface mountable (or flush mountable with optional bezel).
- Options include:
  - Beacon (can be fitted to the top of the telephone or mounted nearby).
  - Flush mount bezel.

#### PRODUCT CODES:

- BVOCET - green emergency telephone, push door.
- BVOCETL - green emergency telephone, lock door.
- BVOCETB - push door + beacon.
- BVOCETLB - lock door + beacon.
- BVOCETBEZ - green bezel to enable flush mounting.



## OMNICARE REMOTE SPECIFICATION:

	Fire Telephone
Product code	BVOCET & BVOCETL
Power supply	12-40V DC self powered from ring circuit
Power consumption	30mA @ 35V typical
Weight	4kg
Humidity range	95% non-condensing
Temperature range	-10°C to +40°C
Indicators	System healthy
Finish	Green
Dimensions mm WxHxD	130 x 350 x 100
Bezel dimensions mm WxH (radius)	170 x 390 x (20)
Bezel cut out mm WxHxD	138 x 358
Knockouts/cable entry points	20mm & 25mm
Mounting position	Emergency telephones should be placed at a height of 1.3m-1.4m

## SYSTEM REQUIREMENTS:

- Fire rated enhanced four core, colour coded, cable with a screen must be used for fire fighting systems.
- Standard fire resisting cables could be considered suitable for:
  - EVC systems for use in disabled refuges but not for fire-fighting in (a) sprinklered buildings; (b) unsprinklered buildings less than 30m in height, provided that evacuation takes place in three or fewer phases.
  - Underground sections of cabling at sports and similar venues.
- Up to 200m cable run between remote units and master control panel as standard.
- A repeater unit (BVFREPEM) must be used if distance between remotes exceeds 200m.
- Disabled refuge, advance disabled refuge, fire telephone, emergency/steward telephone, combined DRS/fire telephone and toilet alarm units can be placed on the same loop.
- A ring circuit configuration must be used to wire the remote units. Typically 20-30 remotes per loop.
- Repeater units (BVFREPEM) are used to connect the toilet alarms to the system.

# BALDWIN BOX▲LL

TEL: +44 (0) 1892 664422  
 FAX: +44 (0) 1892 663146

EMAIL: MAIL@BALDWINBOXALL.CO.UK  
 WEB: WWW.BALDWINBOXALL.CO.UK

BALDWIN BOXALL COMMUNICATIONS LTD  
 WEALDEN INDUSTRIAL ESTATE,  
 FARNINGHAM ROAD, CROWBOROUGH,  
 EAST SUSSEX, TN6 2JR, UNITED KINGDOM.



WE RESERVE THE RIGHT TO CHANGE THE PRODUCT SPECIFICATION WITHOUT PRIOR NOTICE OR LIABILITY. DOC NO. 1.001j|0.11