

Omnicare Repeater Unit



The EVC repeater unit - BVOCRIF - enables our DTAKIT disabled toilet alarm products to be added to an Omnicare system. The BVOCRIF also acts as a line booster to enable longer cable lengths between outstations and/or control panels.

Omnicare

BENEFITS & FEATURES:

As an interface for the DTA toilet alarm kit:

- Use the BVOCRIF as an interface for the DTAKIT (three part) toilet alarm system.
- Up to two DTAKITs can be fitted to each BVOCRIF repeater (will show as one point on the control panel).
- As an alternative, one DTAKIT and an additional pull cord can be fitted to a BVOCRIF. Useful for rooms with two points of call, e.g. a toilet cubicle with a shower area.
- Replaces the BVFREPEM repeater unit (formerly used to connect the BVOCDTA products to an Omnicare system).
- The DTAKIT is suitable for installation on any Omnicare system via the BVOCRIF repeater.

General:

- The BVOCRIF can act as a booster unit to enable cable runs exceeding 200 metres between remote units (outstations) and/or control panels.
- Repeater units are not seen as an 'address' on the control panel (unless connected to a disabled toilet alarm).
- An internal termination board includes loop through connector for testing site wiring.
- Self powered from the ring circuit.
- Surface mountable.
- Zintec finish.

Specifications:

Power supply	12-40V DC self powered from ring circuit
Power consumption	30mA @ 30V typical
Humidity range	95% non-condensing
Temperature range	-10°C to +40°C
Indicators	System healthy & DTA active
Finish	Zintec
Dimensions mm W x H x D	150 x 120 x 50
Weight kg	0.76
Knockouts/cable entry points mm	4 x 20



BALDWIN BOXALL
LEADING THE WAY TO SAFETY

Baldwin Boxall Communications Ltd
Wealden Industrial Estate, Farningham Road,
Crowborough, East Sussex, TN6 2JR, United Kingdom

T: +44 (0) 1892 664422
E: hello@baldwinboxall.co.uk
W: www.baldwinboxall.co.uk